

# EAT•N

# Powerware

## Powerware 5125 Uninterruptible Power System

Product Focus

1000-2200 VA powerful protection for networked office servers



### Product Snapshot

Power Rating:	1000-2200 VA
Voltage:	240 VAC
Frequency:	50/60 Hz
Configuration:	Plug-and-play tower
Topology:	Line-interactive

### Features

- Extended backup time
- Connectivity options
- Software Suite bundled
- ABM™, prolongs battery life by 50%
- Load segments allow scheduled shutdown of non-critical loads
- Multiple Australian outlets for ease of connection

### Options

- ConnectUPS-X Web/SNMP card with in-built switching hub
- External battery cabinets
- USB card
- Relay card

### Typical Applications

- Small network
- Servers
- Network devices

Designed to ensure clean power and reliable operation of all kinds of IT devices in the network system, Powerware 5125 protects your equipment against five of the nine most common power problems that can harm your equipment or result in corrupted data.

The PW5125 offers the features needed for cost effective network protection and comes with the proven reliability users have come to expect from Powerware products. In addition to a reliable shutdown solution, Powerware 5125 offers extended runtime capability as well as enhanced connectivity options to manage and monitor the UPS remotely.

# Technical Specifications

<b>POWERWARE 5125</b>					
Rating	1000VA	1500VA	2000VA	2200VA	
Part Number	51251000A	51251500A	51252000A	51252200A	
Capacity (VA/Watts)	1000/700	1500/1050	2000/1400	2200/1600	
Dimensions WxDxH (mm)	162x401x250	162x467x250	205x493x250	205x493x250	
Weight (kg)	16	23	31	31	
Input Connection	IEC320/10A	IEC320/10A	IEC320/10A	IEC320/16A	
Output Connection	4 x AUST. 10A	4 x AUST. 10A	6 x AUST. 10A	6 x AUST.10A	
Typical runtime (Full load)	5 min	6 min	6 min	5 min	
<b>Operational</b>					
Nominal input voltage (Vac)	220/230/240 Vac				
Input voltage range	166-276 VAC (+15/-30% of nominal)				
Operating frequency	50/60 Hz auto sensing				
Input power factor	Same as load				
Nominal output voltage	220/230/240 VAC				
Output voltage regulation	-10%/+6% of selected nominal voltage				
Overload capacity	110% 3 min; 150% 10 cycles				
Efficiency	95%				
<b>User interface</b>					
LED Information	LED display				
Standard communication ports	RS232				
Optional	SNMP/WEB card, USB card, relay cards				
<b>Environmental</b>					
Operating temperature	0°C - +40°C				
Storage temperature	-15°C - +55°C				
Altitude	< 3000 m				
Audible noise at 1 metre	< 45dB normal mode < 50dB battery mode				
<b>Certification</b>					
Markings	CE/GS/UL/C-Tick				
Safety	EN 50091-1-1 & UL 1778				
EMC	EN 50091-2, EN6100-3-2				
<b>Battery Runtimes (in minutes full load/half load)*</b>					
Model	Standard Internal Batteries	1 EBM	2 EBMs	3 EBMs	4 EBMs
1000VA	5/16	48/110	100/220	170/6h	4h/8h
1500VA	6/17	33/79	63/146	92/174	120/201
2000VA	6/15	30/70	60/190	90/215	120/240
2200VA	5/14	26/60	55/170	81/198	106/224

\* Up to 4 EBMs can be connected. EBM runtimes include internal batteries. This guide provides typical application information. Battery run times are approximate and may vary with equipment, configuration, battery age, temperature, etc.

HEAD OFFICE  
Eaton Power Quality Pty Ltd  
10 Kent Road  
Mascot NSW 2020  
Phone: +61 2 9693 9366  
Fax: +61 2 8338 1159

www.powerware.com.au

SALES OFFICES  
Queensland  
Phone: +61 7 3891 1211  
Fax: +61 7 3891 2492

Victoria  
Phone: + 61 3 9706 5662  
Fax: + 61 3 9794 9150

South Australia  
Phone: +61 8 8347 3622  
Fax: +61 8 8445 6328

Western Australia  
Phone: +61 8 9240 5655  
Fax: + 61 8 9240 5644

Auckland New Zealand  
Phone: + 64 9 273 3970  
Fax: +64 9 273 3980

Powerware and ABM are trade names, trademarks and/or service marks of Eaton Power Quality Corporation or its subsidiaries and affiliates. All other trademarks are property of their respective owners.



**Powerware**